



Synco™ 700



## Bus Operator Unit

**RMZ792**

**Communicating operator unit for operating up to 150 controllers, room units and central units from the Synco™ 700 range via Konnex bus.  
Favorite pages can be freely defined. Powered via Konnex bus or external AC 24 V power supply. Designed for fixed installation or mobile use.**

### Use

- Central remote operation of several devices of the Synco™ 700 range and of RXB individual room controllers in a Konnex network
- Operation of Synco™ devices from a remote location
- Mobile service unit for setting the parameters of plant

### Note

The RMZ792 bus operator unit is not suited for commissioning Synco™ 700 controllers. Commissioning of plant is made with the RMZ790 or RMZ791 operator units or the OCI700.1 service tool.

### Functions

#### Device list

- Device list with a maximum of 150 units
- Automatic device search run
- Automatic or manual sorting of device list
- Naming or renaming of devices
- Deletion of individual devices or of the entire device list

- Favorite pages**
  - Maximum 20 favorite pages for compiling the most important plant values
  - Assignment of up to 10 plant values per favorite page
  - Naming or renaming pages and plant values
  - Sorting favorite pages
  - Deletion of favorite pages
  
- Handling faults**
  - Fault indication by red LED and symbol
  - Acknowledgement and resetting of faults
  - List for indicating a maximum of 20 pending faults
  
- Operating levels**
  - 4 operating levels: Info, user, service, and password level
  - User, service and password level with individual password protection
  
- Service functions**
  - User-defined business card for service address / telephone
  - Data backup
  
- Bus functions**
  - Automatic device address search
  - Display of fault status messages from other devices on the bus
  - Display of system time and date
  
- Supported devices**
  - RMx7... controllers of the Synco™ 700 range
  - RXB2... and RXL2... individual room controllers
  - QAW7... room units
  - OZW77... central communication units
  
- Languages**
  - German, English, French, Italian, Dutch, Polish, Czech, Slovakian, Hungarian, Spanish, Danish, Norwegian, Swedish, Finnish, Greek, Russian, Romanian, Slovenian, Serbian, Croatian
  
- Power supply**
  - Via Konnex bus or external AC 24 V power supply

### Type summary

<i>Designation</i>	<i>Type reference</i>	<i>Languages</i>
Bus operator unit	<b>RMZ792</b>	de, en, fr, it, nl, pl, cs, sk, hu, es, da, no, sv, fi, el, ru, ro, sl, sr, hr
Memory card for RMZ792	<b>RMA792</b>	de, en, fr, it, nl, pl, cs, sk, hu, es, da, no, sv, fi, el, ru, ro, sl, sr, hr

### Ordering and delivery

When ordering, please give name and type reference:

Bus operator unit **RMZ792**.

The RMA792 memory card is included in the scope of delivery.

For updating languages and device descriptions, a **new** RMA792 memory card must be ordered.